



TL-R400S

Drive Bay	4 x 3.5-inch SATA 6Gb/s, 3Gb/s
Drive Compatibility	3.5-inch SATA hard disk drives 2.5-inch SATA solid state drives
Audio Alert On/Off Switch	Yes
Form Factor	1U Short Depth Rackmount
Host Interface	1 x SFF-8088
LED Indicators	HDD 1-4, Status, Link, Fan error
Buttons	Power switch
Dimensions (HxWxD)	43.9 × 438.9 × 291.1 mm Excludes ear hook and the protruding part of the Power Supply Unit.
Weight (Net)	3.98 kg
Weight (Gross)	5.38 kg
Max. number of HDDs/SSDs supported	4
Hard Drive Type	3.5-inch SATA hard disk drives 2.5-inch SATA hard disk drives 2.5-inch SATA solid state drives
Operating Temperature	0 - 40 °C (32°F - 104°F)
Storage Temperature	-20 - 70°C (-4°F - 158°F)
Relative Humidity	5-95% RH non-condensing, wet bulb: 27°C (80.6°F)
Power Supply Unit	100W PSU, 100 - 240V
Power Consumption: Operating Mode, Typical	25.07 W Tested fully populated with Seagate ST6000NM0024 hard drives.
Fan Mode Switch	Yes (Auto, high, medium, low)
Fan	2 x 40mm, 12VDC

System Warning	Buzzer
Kensington Security Slot	Yes

Note: Use only QNAP memory modules to maintain system performance and stability. For NAS devices with more than one memory slot, use QNAP modules with identical specifications.

Warning: Using unsupported modules may degrade performance, cause errors, or prevent the operating system from starting. QNAP reserves the right to replace partial parts or accessories if the original is no longer available from its manufacturer/supplier. Any replacement would be fully tested and verified to meet strict compatibility and stability guidelines and will deliver identical performance to the original.

The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI trade dress and the HDMI Logos are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

Product images are for illustrative purposes only and may differ from the actual product. Due to differences in monitors, colors of products may also appear different to those shown on the site.

Designs and specifications are subject to change without notice.